



Be-Tech  
Premium RF Card Digital Door Lock  
with anti-panic

- Digital Mortise Lock
- RF Card & Touchpad
- 60mm Backset Mortise
- Coffee Gold



**Unlock your life with smart solution**  
Leave your home security to Be-Tech



### Various access(PIN,RF cards)

Be-Tech V3A8MT has two access solutions, RF Card key or PIN code for your convenience.



### Invisible keypad

Keypad number can be seen only when you touch the screen with your palm.



### Fake PIN code

You can make an instant PIN code for security.



### Operation status notification

Whenever any operation is made, the LED indicator informs you what is happened through different color and blinking.



### Automatic locking

Door lock will be locked automatically after opening door a few seconds (Manual operation is also available)



### Missing key invalidation

Once you lose your key, it has no validation as long as you re-register rest of your keys.



### Anti-panic exit system

For convenience and in case of emergency, allows you to open the door by simply turning its handle from inside.



### Alarm (Incorrect PIN code attempt)

Alarm will on and last 60 seconds if anyone attempts to open the lock by key in 4 times incorrect PIN code.



### Low battery warning signal

A continuous "beep" sound during door access will alert you to replace batteries.



### Scramble code

You can meaningless number prior to the right code when there is chance of exposing it to others.



### Mechanical key override

For emergency, it can also be unlocked with a mechanical key.



Convenient



Model



Reliable



Safe



## Specification

Parts	Specifications	Remarks
Front(Front Body)	73(W)×333(H)×21(D)(75 with door handle)mm, Zinc Alloy	Temperature: Workable -20℃~60℃ Humidity: Workable 20%~95%
Back(Back Body)	79(W)×333(H)×25(D)(67 with door handle)mm, Zinc Alloy	
Door Thickness	Applicable Range 40-50mm	
Handle	Zinc Alloy	
Card Keys	Up to 40 keys(1 Master key & 39 User keys)	
User Codes	4~9Digits(0000~000000000)	10 Groups
Battery	4×1.5V AA alkaline batteries(Operating voltage:4.2~6V)	Last up to 12 months(10 times used a day)
Lock case	Stainless Steel	

Contact us:

Smart Your Life



Guangdong Be-Tech Security Systems Limited

No.17, KeYuan 3 Road, Ronggui

Shunde High-Tech Zone, Foshan,

Guangdong 528306, P.R.China

Tel:+86 757 28376123 | Fax:+86 757 28308823

E-mail:export@be-tech.com.cn | www.betech-security.com

Specifications may change without notice.

ID:03-BTRA44C1412-E1-01